

# Apollo Coaster Pager

## Hospitality Series



*"Your Source for Pagers"*

Visit Our Website at:

[www.WirelessMessaging.com](http://www.WirelessMessaging.com)

**NOTE:** Frequency Required when Ordered



P/N= 0410-1001

Perfect for Restaurants and Waiting Rooms, etc.

### Key Features:

- Synthesized or Crystal Type
- Tone / Vibration / Flash Only
- Flash with 13 LED Alert
- Two LED (Heartbeat, Alert, Out of Range and Low Battery)
- Rechargeable: Ni-MH Battery
- Over-the-Air "Off"
- Programmable Alert Type
- Programmed by PC Software
- Advertising Center Sticker
- Continuous Beep Option
- **Requires:** Charging Base (Sold Separately)  
P/N= 0410-1009

### Specifications:

- Model: AL-205 (Also called the Coaster Pager)
- Frequency: 408-473 MHz and 138-174 MHz
- Paging Sensitivity: 512bps - 5 $\mu$ V/M, 1200bps - 7 $\mu$ V/M, 2400bps - 9 $\mu$ V/M
- Pager Baud Rate: 512 / 1200 / 2400bps for POCSAG,
- Channel Spacing: 25 KHz Wide Band (WB)
- Code Format: POCSAG
- Spurious Rejection: 40db below carrier
- Alert Tone Loudness: 85db @ 10 cm
- Cap Codes: 4 Cap Codes for POCSAG
- Coaster Pager Weight: Approx. 115 Grams (w/o Battery)
- Charging Base Weight: Approx. 75 Grams
- Dimension: 109.08 Dia. x 15.9 (H) mm



Coaster-Pager Charging Base  
Charges 10 Pagers per Base